

# PONTIAC COIL DSL TRANSFORMERS

## 6A475



- For use with the following:

**Centillium Technologies *CopperFlite™* ADSL chipsets**

- Central Office (C.O.) Line coupling transformer.
- Designed to meet EN60950 requirements for Supplementary Isolation.

### ELECTRICAL SPECIFICATION\*

Inductance @ 10kHz 0.1 Vrms	Leakage Inductance @ 100 kHz 0.1 Vrms	Turns Ratio	DC Resistance (max.)		Isolation Voltage Primary : Secondary
1 - 4 (s/c 2-3)	1 - 4 (s/c 2-3, 8-9, 10-7)	1 - 4 : 10 - 7	1 - 4 (s/c 2-3)	10 - 7 (s/c 8-9)	1 - 10 (1 sec.)
<b>450 <math>\mu</math>H <math>\pm</math> 5%</b>	<b>&lt; 6.0 <math>\mu</math>H</b>	<b>1.8 : 1</b>	<b>1.80 <math>\Omega</math></b>	<b>0.60 <math>\Omega</math></b>	<b>1875 Vrms</b>

\* At 23°C

SCHEMATIC	MECHANICAL SPECIFICATION	
<p style="text-align: center;">Line      Device</p> <p style="text-align: center;">Turns Ratio    1.8 : 1</p> <p style="text-align: center;"><i>This component is currently under development :</i></p> <p>Approximate Weight.....7 grams</p>	<h3 style="text-align: center; color: red;">Surface Mount Style – 6A475</h3> <div style="display: flex; justify-content: space-around;"> <div style="text-align: center;"> <p>TOP VIEW</p> </div> <div style="text-align: center;"> <p>SIDE VIEW</p> </div> <div style="text-align: center;"> <p>PAD LAYOUT</p> </div> </div> <p style="text-align: center;">Dimensions in mm</p>	

#### Pontiac Coil – Europe Ltd.

PO Box 246  
Queens Drive Industrial Estate  
Nottingham NG2 1NQ

#### United Kingdom

Tel: +44 (0) 115 986 1126  
Fax: +44 (0) 115 986 0563

#### Pontiac Coil, Inc.

5800 Moody Drive  
Clarkston  
Michigan 48348

#### USA

Tel: +1 248 922 2203  
Fax: +1 248 922 1315

#### Local Distributors available in:

**Australia, Finland, Israel, Italy, Malaysia, Norway, Singapore, Sweden and Taiwan.**

For details contact **Pontiac Coil - Europe Ltd.**

[sales@pontiaccoil.co.uk](mailto:sales@pontiaccoil.co.uk)

[www.pontiaccoil.co.uk](http://www.pontiaccoil.co.uk)